

855 Purchase Order Acknowledgment

X12/V5010/855: 855 Purchase Order Acknowledgment

Author:	SPS Commerce
Company:	Woodcraft
Created:	11/27/2012
Modified:	1/11/2013
Notes:	

855 Purchase Order Acknowledgment

Functional Group=**PR**

Purpose: This X12 Transaction Set contains the format and establishes the data contents of the Purchase Order Acknowledgment Transaction Set (855) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to a seller's acknowledgment of a buyer's purchase order. This transaction set can also be used as notification of a vendor generated order. This usage advises a buyer that a vendor has or will ship merchandise as prearranged in their partnership.

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
0100	ST	Transaction Set Header	M	1			Must use
0200	BAK	Beginning Segment for Purchase Order Acknowledgment	M	1			Must use
0500	REF	Reference Information	M	2			Must use
0600	PER	Administrative Communications Contact	O	3			Used
1500	DTM	Date/Time Reference	O	1			Used
LOOP ID - N9					<u>1</u>		
2800	N9	Extended Reference Information	M	1			Must use
2900	MTX	Text	M	1			Must use
LOOP ID - N1					<u>200</u>		
3000	N1	Party Identification	O	1			Used
3200	N3	Party Location	O	2			Used
3300	N4	Geographic Location	O	1			Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - PO1					<u>100000</u>	<u>N2/0100L</u>	
0100	PO1	Baseline Item Data	M	1		N2/0100	Must use
LOOP ID - PID					<u>1000</u>		
0500	PID	Product/Item Description	M	1			Must use
LOOP ID - ACK					<u>1</u>		
2700	ACK	Line Item Acknowledgment	M	1			Must use

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - CTT					<u>1</u>	<u>N3/0100L</u>	
0100	CTT	Transaction Totals	M	1		N3/0100	Must use
0300	SE	Transaction Set Trailer	M	1			Must use

Notes:

2/0100L PO102 is required.

2/0100 PO102 is required.

3/0100L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

3/0100 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

General Usage:

All orders must be acknowledged with a Purchase Order Acknowledgement (855) or shipped with the Advanced Shipment Notice (856) transmitted **within 48 hours** of receipt.

ST Transaction Set Header

Pos: 0100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use
Description: Code uniquely identifying a Transaction Set						
CodeList Summary (Total Codes: 318, Included: 1)						
Code Name						
855 Purchase Order Acknowledgment						
ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set						

Semantics:

1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition. When used, this implementation convention reference takes precedence over the implementation reference specified in the GS08.

BAK Beginning Segment for Purchase Order Acknowledgment

Pos: 0200	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 5

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Acknowledgment Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BAK01	353	Transaction Set Purpose Code	M	ID	2/2	Must use
Description: Code identifying purpose of transaction set						
CodeList Summary (Total Codes: 66, Included: 1)						
Code Name						
00 Original						
BAK02	587	Acknowledgment Type	M	ID	2/2	Must use
Description: Code specifying the type of acknowledgment						
CodeList Summary (Total Codes: 15, Included: 3)						
Code Name						
AC Acknowledge - With Detail and Change						
User Note 1:						
<i>PO1 and ACK segments required</i>						
AD Acknowledge - With Detail, No Change						
User Note 1:						
<i>PO1 and ACK segments required</i>						
RD Reject with Detail						
User Note 1:						
<i>PO1 and ACK segments required</i>						
BAK03	324	Purchase Order Number	M	AN	1/22	Must use
Description: Identifying number for Purchase Order assigned by the orderer/purchaser						
BAK04	373	Date	M	DT	8/8	Must use
Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year						
User Note 1: <i>Purchase Order Date</i>						
BAK09	373	Date	M	DT	8/8	Must use
Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year						
User Note 1: <i>PO Acknowledgement Date</i>						

Semantics:

1. BAK04 is the date assigned by the purchaser to purchase order.

2. BAK08 is the seller's order number.
3. BAK09 is the date assigned by the sender to the acknowledgment.

REF Reference Information

Pos: 0500	Max: 2
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To specify identifying information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
REF01	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

User Note 1: *Vendor Number is Mandatory
Customer Order Number is required for Drop Ship shipments*

CodeList Summary (Total Codes: 1731, Included: 2)

Code Name

CO Customer Order Number

User Note 1:

Customer Order Number is required for Drop Ship shipments.

IA Internal Vendor Number

User Note 1:

Vendor Number is required for all shipments (Mandatory).

REF02	127	Reference Identification	X	AN	1/50	Used
-------	-----	--------------------------	---	----	------	------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

PER Administrative Communications Contact

Pos: 0600	Max: 3
Heading - Optional	
Loop: N/A	Elements: 8

User Option (Usage): Used

Purpose: To identify a person or office to whom administrative communications should be directed

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>				
PER01	366	Contact Function Code	M	ID	2/2	Must use				
<p>Description: Code identifying the major duty or responsibility of the person or group named</p> <p>CodeList Summary (Total Codes: 238, Included: 1)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>IC</td> <td>Information Contact</td> </tr> </tbody> </table>							<u>Code</u>	<u>Name</u>	IC	Information Contact
<u>Code</u>	<u>Name</u>									
IC	Information Contact									
PER02	93	Name	X	AN	1/60	Used				
<p>Description: Free-form name</p>										
PER03	365	Communication Number Qualifier	X	ID	2/2	Used				
<p>Description: Code identifying the type of communication number</p> <p>CodeList Summary (Total Codes: 42, Included: 1)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>TE</td> <td>Telephone</td> </tr> </tbody> </table>							<u>Code</u>	<u>Name</u>	TE	Telephone
<u>Code</u>	<u>Name</u>									
TE	Telephone									
PER04	364	Communication Number	C	AN	1/256	Used				
<p>Description: Complete communications number including country or area code when applicable</p>										
PER05	365	Communication Number Qualifier	X	ID	2/2	Used				
<p>Description: Code identifying the type of communication number</p> <p>CodeList Summary (Total Codes: 42, Included: 1)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>FX</td> <td>Facsimile</td> </tr> </tbody> </table>							<u>Code</u>	<u>Name</u>	FX	Facsimile
<u>Code</u>	<u>Name</u>									
FX	Facsimile									
PER06	364	Communication Number	C	AN	1/256	Used				
<p>Description: Complete communications number including country or area code when applicable</p>										
PER07	365	Communication Number Qualifier	X	ID	2/2	Used				
<p>Description: Code identifying the type of communication number</p> <p>CodeList Summary (Total Codes: 42, Included: 1)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>EM</td> <td>Electronic Mail</td> </tr> </tbody> </table>							<u>Code</u>	<u>Name</u>	EM	Electronic Mail
<u>Code</u>	<u>Name</u>									
EM	Electronic Mail									
PER08	364	Communication Number	C	AN	1/256	Used				
<p>Description: Complete communications number including country or area code when applicable</p>										

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
		applicable				

Syntax Rules:

1. P0304 - If either PER03 or PER04 is present, then the other is required.
2. P0506 - If either PER05 or PER06 is present, then the other is required.
3. P0708 - If either PER07 or PER08 is present, then the other is required.

User Note 1:

At least one of PER02, PER04, PER06, or PER08 are required.

DTM Date/Time Reference

Pos: 1500	Max: 1
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

Purpose: To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use

Description: Code specifying type of date or time, or both date and time

CodeList Summary (Total Codes: 1280, Included: 1)

Code Name

068 Current Schedule Ship

DTM02	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

Loop Extended Reference Information

Pos: 2800	Repeat: 1
Optional	
Loop: N9	Elements: N/A

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2800	N9	Extended Reference Information	M	1		Must use
2900	MTX	Text	M	1		Must use

N9 Extended Reference Information

Pos: 2800	Max: 1
Heading - Mandatory	
Loop: N9	Elements: 2

User Option (Usage): Must use

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use
		Description: Code qualifying the Reference Identification				
		CodeList Summary (Total Codes: 1731, Included: 1)				
		Code Name				
		L1		Letters or Notes		
N903	369	Free-form Description	M	AN	1/45	Must use

Description: Free-form descriptive text

User Note 1: *The following reference identifier (N903) values will be sent to identify the message type used in the MTX segment that follows:*
 . PO ACKNOWLEDGEMENT NOTES

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

MTX Text

Pos: 2900	Max: 1
Heading - Mandatory	
Loop: N9	Elements: 1

User Option (Usage): Must use
Purpose: To specify textual data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MTX02	1551	Textual Data	M	AN	1/4096	Must use

Description: To transmit large volumes of message text

User Note 1: *Maximum length of characters allowed = 264*

Syntax Rules:

1. C0102 - If MTX01 is present, then MTX02 is required.
2. C0302 - If MTX03 is present, then MTX02 is required.
3. C0504 - If MTX05 is present, then MTX04 is required.

Semantics:

1. MTX05 is the number of lines to advance before printing.

Comments:

1. If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Loop Party Identification

Pos: 3000	Repeat: 200
Optional	
Loop: N1	Elements: N/A

User Option (Usage): Used

Purpose: To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
3000	N1	Party Identification	O	1		Used
3200	N3	Party Location	O	2		Used
3300	N4	Geographic Location	O	1		Used

N1 Party Identification

Pos: 3000	Max: 1
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

CodeList Summary (Total Codes: 1500, Included: 2)

<u>Code</u>	<u>Name</u>
ST	Ship To
VN	Vendor

N102	93	Name	M	AN	1/60	Must use
------	----	------	---	----	------	----------

Description: Free-form name

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Party Location

Pos: 3200	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used

Purpose: To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	C	AN	1/55	Used
		Description: Address information				
N302	166	Address Information	O	AN	1/55	Used
		Description: Address information				

User Note 1:

If N302 is present, then N301 is required.

N4 Geographic Location

Pos: 3300	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

User Option (Usage): Used

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Used
		Description: Free-form text for city name				
N402	156	State or Province Code	C	ID	2/2	Used
		Description: Code (Standard State/Province) as defined by appropriate government agency				
N403	116	Postal Code	O	ID	3/15	Used
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				
N404	26	Country Code	X	ID	2/3	Used
		Description: Code identifying the country				

Syntax Rules:

1. E0207 - Only one of N402 or N407 may be present.
2. C0605 - If N406 is present, then N405 is required.
3. C0704 - If N407 is present, then N404 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

Loop Baseline Item Data

Pos: 0100	Repeat: 100000
Conditional	
Loop: PO1	Elements: N/A

User Option (Usage): Used

Purpose: To specify basic and most frequently used line item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	PO1	Baseline Item Data	M	1		Must use
0500		Loop PID	M		1000	Must use
2700		Loop ACK	M		1	Must use

User Note 1:

If BAK02 = AC, AD, RD, Then the PO1 and ACK segments are required.

PO1 Baseline Item Data

Pos: 0100	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 10

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	Assigned Identification	O	AN	1/20	Used
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
PO102	380	Quantity	O	R	1/15	Used
		Description: Numeric value of quantity				
PO103	355	Unit or Basis for Measurement Code	C	ID	2/2	Used
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		CodeList Summary (Total Codes: 844, Included: 2)				
		<u>Code</u>	<u>Name</u>			
		CA	Case			
		EA	Each			
PO104	212	Unit Price	C	R	1/17	Used
		Description: Price per unit of product, service, commodity, etc.				
PO106	235	Product/Service ID Qualifier	M	ID	2/2	Must use
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		CodeList Summary (Total Codes: 519, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		CB	Buyer's Catalog Number			
PO107	234	Product/Service ID	M	AN	1/48	Must use
		Description: Identifying number for a product or service				
PO108	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		CodeList Summary (Total Codes: 519, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		VN	Vendor's (Seller's) Item Number			
PO109	234	Product/Service ID	C	AN	1/48	Used
		Description: Identifying number for a product or service				
PO110	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in				

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
		Product/Service ID (234)				
		CodeList Summary (Total Codes: 519, Included: 1)				
		Code		Name		
		UP		UCC - 12		
		User Note 1:				
		The <i>UP</i> qualifier is used to represent any of the family of GTIN (Global Trade Item Number) data structures:				
		GTIN-12 (UPC-12)				
		GTIN-13 (EAN/UCC-13)				
		GTIN-14 (ITF14)				
		GTIN-8 (EAN/UCC-8)				
PO111	234	Product/Service ID	C	AN	1/48	Used

Description: Identifying number for a product or service

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Semantics:

1. PO102 is quantity ordered.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

User Note 1:

When ACK01 = IP, PO103 and PO104 are required.

Loop Product/Item Description

Pos: 0500	Repeat: 1000
Mandatory	
Loop: PID	Elements: N/A

User Option (Usage): Must use

Purpose: To describe a product or process in coded or free-form format

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0500	PID	Product/Item Description	M	1		Must use

PID Product/Item Description

Pos: 0500	Max: 1
Detail - Mandatory	
Loop: PID	Elements: 3

User Option (Usage): Must use

Purpose: To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID01	349	Item Description Type	M	ID	1/1	Must use

Description: Code indicating the format of a description

CodeList Summary (Total Codes: 3, Included: 1)

Code Name

F Free-form

PID02	750	Product/Process Characteristic Code	O	ID	2/3	Used
-------	-----	-------------------------------------	---	----	-----	------

Description: Code identifying the general class of a product or process characteristic

CodeList Summary (Total Codes: 238, Included: 1)

Code Name

08 Product

PID05	352	Description	M	AN	1/80	Must use
-------	-----	-------------	---	----	------	----------

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.
3. PID07 specifies the individual code list of the agency specified in PID03.

Loop Line Item Acknowledgment

Pos: 2700	Repeat: 1
Mandatory	
Loop: ACK	Elements: N/A

User Option (Usage): Must use

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2700	ACK	Line Item Acknowledgment	M	1		Must use

ACK Line Item Acknowledgment

Pos: 2700	Max: 1
Detail - Mandatory	
Loop: ACK	Elements: 5

User Option (Usage): Must use

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ACK01	668	Line Item Status Code	M	ID	2/2	Must use

Description: Code specifying the action taken by the seller on a line item requested by the buyer

CodeList Summary (Total Codes: 26, Included: 7)

Code Name

- DR Item Accepted - Date Rescheduled
- IA Item Accepted
- IB Item Backordered
- IP Item Accepted - Price Changed
- IQ Item Accepted - Quantity Changed
- IR Item Rejected
- R2 Item Rejected, Invalid Item Product Number

ACK02	380	Quantity	X	R	1/15	Used
-------	-----	----------	---	---	------	------

Description: Numeric value of quantity

ACK03	355	Unit or Basis for Measurement Code	X	ID	2/2	Used
-------	-----	------------------------------------	---	----	-----	------

Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken

CodeList Summary (Total Codes: 844, Included: 2)

Code Name

- CA Case
- EA Each

ACK04	374	Date/Time Qualifier	X	ID	3/3	Used
-------	-----	---------------------	---	----	-----	------

Description: Code specifying type of date or time, or both date and time

CodeList Summary (Total Codes: 1280, Included: 1)

Code Name

- 068 Current Schedule Ship

ACK05	373	Date	X	DT	8/8	Used
-------	-----	------	---	----	-----	------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

Syntax Rules:

1. P0203 - If either ACK02 or ACK03 is present, then the other is required.
2. C0405 - If ACK04 is present, then ACK05 is required.
3. P0708 - If either ACK07 or ACK08 is present, then the other is required.

4. P0910 - If either ACK09 or ACK10 is present, then the other is required.
5. P1112 - If either ACK11 or ACK12 is present, then the other is required.
6. P1314 - If either ACK13 or ACK14 is present, then the other is required.
7. P1516 - If either ACK15 or ACK16 is present, then the other is required.
8. P1718 - If either ACK17 or ACK18 is present, then the other is required.
9. P1920 - If either ACK19 or ACK20 is present, then the other is required.
10. P2122 - If either ACK21 or ACK22 is present, then the other is required.
11. P2324 - If either ACK23 or ACK24 is present, then the other is required.
12. P2526 - If either ACK25 or ACK26 is present, then the other is required.
13. P2728 - If either ACK27 or ACK28 is present, then the other is required.
14. C282729 - If ACK28 is present, then ACK27 and ACK29 are required.

Semantics:

1. ACK29 Industry Reason Code may be used to identify the item status. In addition, it may be used in conjunction with ACK01 to further clarify the status.

User Note 1:

If either ACK02 or ACK03 are present, then the other is required.

If ACK04 or ACK05 or present, then the other is required.

If ACK01= DR, IQ, or IB then ACK02 and ACK03 are required .

If ACK01=DR, IB then ACK05 is required.

Loop Transaction Totals

Pos: 0100	Repeat: 1
Mandatory	
Loop: CTT	Elements: N/A

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	CTT	Transaction Totals	M	1		Must use

CTT Transaction Totals

Pos: 0100	Max: 1
Summary - Mandatory	
Loop: CTT	Elements: 1

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use

Description: Total number of line items in the transaction set

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

SE Transaction Set Trailer

Pos: 0300	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	N0	1/10	Must use
Description: Total number of segments included in a transaction set including ST and SE segments						
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set						

Comments:

- SE is the last segment of each transaction set.