

855 Purchase Order Acknowledgment

X12/V5010/855 : 855 Purchase Order Acknowledgment

Author:	SPS Commerce
Company:	Hubert Company

Table of Contents

855	Purchase Order Acknowledgment	1
ST	Transaction Set Header	3
BAK	Beginning Segment for Purchase Order Acknowledgment	4
CUR	Currency	6
REF	Reference Information	7
PER	Administrative Communications Contact	8
FOB	F.O.B. Related Instructions	10
DTM	Date/Time Reference	11
TD5	Carrier Details (Routing Sequence/Transit Time)	12
N9	Loop Extended Reference Information	13
N9	Extended Reference Information	14
MTX	Text	15
N1	Loop Party Identification	16
N1	Party Identification	17
N2	Additional Name Information	18
N3	Party Location	19
N4	Geographic Location	20
PER	Administrative Communications Contact	21
PO1	Loop Baseline Item Data	22
PO1	Baseline Item Data	23
PID	Loop Product/Item Description	26
PID	Product/Item Description	27
ACK	Loop Line Item Acknowledgment	28
ACK	Line Item Acknowledgment	29
N9	Loop Extended Reference Information	32
N9	Extended Reference Information	33
MTX	Text	34
SE	Transaction Set Trailer	35

855 Purchase Order Acknowledgment

Functional Group=PR

Purpose: This X12 Transaction Set contains the format and establishes the data contents of the Purchase Order Acknowledgment Transaction Set (855) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to a seller's acknowledgment of a buyer's purchase order. This transaction set can also be used as notification of a vendor generated order. This usage advises a buyer that a vendor has or will ship merchandise as prearranged in their partnership.

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
0100	ST	Transaction Set Header	M	1			Must use
0200	BAK	Beginning Segment for Purchase Order Acknowledgment	M	1			Must use
0400	CUR	Currency	O	1			Used
0500	REF	Reference Information	M	1			Must use
0600	PER	Administrative Communications Contact	O	1			Used
0800	FOB	F.O.B. Related Instructions	O	1			Used
1500	DTM	Date/Time Reference	M	1			Must use
2400	TD5	Carrier Details (Routing Sequence/Transit Time)	M	1			Must use
LOOP ID - N9					10		
2800	N9	Extended Reference Information	M	1			Must use
2900	MTX	Text	M	1			Must use
LOOP ID - N1					2		
3000	N1	Party Identification	M	1			Must use
3100	N2	Additional Name Information	O	1			Used
3200	N3	Party Location	M	1			Must use
3300	N4	Geographic Location	M	1			Must use
3500	PER	Administrative Communications Contact	O	1			Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - PO1					100000	N2/0100L	
0100	PO1	Baseline Item Data	M	1		N2/0100	Must use
LOOP ID - PID					1		
0500	PID	Product/Item Description	M	1			Must use
LOOP ID - ACK					5		
2700	ACK	Line Item Acknowledgment	M	1			Must use
LOOP ID - N9					10		
3500	N9	Extended Reference Information	M	1			Must use

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
3600	MTX	Text	M	1			Must use

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
0300	SE	Transaction Set Trailer	M	1			Must use

Notes:

2/0100L PO102 is required.

2/0100 PO102 is required.

ST Transaction Set Header

Pos: 0100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use

Description: Code uniquely identifying a Transaction Set

CodeList Summary (Total Codes: 318, Included: 1)

Code Name

855 Purchase Order Acknowledgment

ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
------	-----	--------------------------------	---	----	-----	----------

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Semantics:

1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition. When used, this implementation convention reference takes precedence over the implementation reference specified in the GS08.

BAK Beginning Segment for Purchase Order Acknowledgment

Pos: 0200	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 6

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Acknowledgment Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BAK01	353	Transaction Set Purpose Code	M	ID	2/2	Must use

Description: Code identifying purpose of transaction set

CodeList Summary (Total Codes: 66, Included: 1)

Code Name

00 Original

BAK02	587	Acknowledgment Type	M	ID	2/2	Must use
-------	-----	---------------------	---	----	-----	----------

Description: Code specifying the type of acknowledgment

CodeList Summary (Total Codes: 15, Included: 3)

Code Name

AC Acknowledge - With Detail and Change

AD Acknowledge - With Detail, No Change

User Note 1:

Used when all items are accepted. All ACK01 values must contain IA.

RD Reject with Detail

User Note 1:

Used when all items are rejected. All ACK01 values must contain IR.

BAK03	324	Purchase Order Number	M	AN	1/22	Must use
-------	-----	-----------------------	---	----	------	----------

Description: Identifying number for Purchase Order assigned by the orderer/purchaser

BAK04	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

BAK05	328	Release Number	O	AN	1/30	Used
-------	-----	----------------	---	----	------	------

Description: Number identifying a release against a Purchase Order previously placed by the parties involved in the transaction

User Note 1: *If a Release Number was sent on the PO, it must be returned on the PO Acknowledgement.*

BAK09	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

Semantics:

1. BAK04 is the date assigned by the purchaser to purchase order.
2. BAK08 is the seller's order number.
3. BAK09 is the date assigned by the sender to the acknowledgment.

CUR Currency

Pos: 0400	Max: 1
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

Purpose: To specify the currency (dollars, pounds, francs, etc.) used in a transaction

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CUR01	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

CodeList Summary (Total Codes: 1500, Included: 1)

Code Name

BY Buying Party (Purchaser)

CUR02	100	Currency Code	M	ID	3/3	Must use
-------	-----	----------------------	---	----	-----	----------

Description: Code (Standard ISO) for country in whose currency the charges are specified

Syntax Rules:

1. C0807 - If CUR08 is present, then CUR07 is required.
2. C0907 - If CUR09 is present, then CUR07 is required.
3. L101112 - If CUR10 is present, then at least one of CUR11 or CUR12 is required.
4. C1110 - If CUR11 is present, then CUR10 is required.
5. C1210 - If CUR12 is present, then CUR10 is required.
6. L131415 - If CUR13 is present, then at least one of CUR14 or CUR15 is required.
7. C1413 - If CUR14 is present, then CUR13 is required.
8. C1513 - If CUR15 is present, then CUR13 is required.
9. L161718 - If CUR16 is present, then at least one of CUR17 or CUR18 is required.
10. C1716 - If CUR17 is present, then CUR16 is required.
11. C1816 - If CUR18 is present, then CUR16 is required.
12. L192021 - If CUR19 is present, then at least one of CUR20 or CUR21 is required.
13. C2019 - If CUR20 is present, then CUR19 is required.
14. C2119 - If CUR21 is present, then CUR19 is required.

Comments:

1. See Figures Appendix for examples detailing the use of the CUR segment.

REF Reference Information

Pos: 0500	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To specify identifying information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
REF01	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1731, Included: 1)

Code Name

IA Internal Vendor Number

REF02	127	Reference Identification	M	AN	1/50	Must use
-------	-----	--------------------------	---	----	------	----------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

PER Administrative Communications Contact

Pos: 0600	Max: 1
Heading - Optional	
Loop: N/A	Elements: 6

User Option (Usage): Used

Purpose: To identify a person or office to whom administrative communications should be directed

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PER01	366	Contact Function Code	M	ID	2/2	Must use
<p>Description: Code identifying the major duty or responsibility of the person or group named</p> <p>CodeList Summary (Total Codes: 238, Included: 1)</p> <p>Code Name</p> <p>IC Information Contact</p>						
PER02	93	Name	C	AN	1/60	Used
<p>Description: Free-form name</p> <p>User Note 1: If PER segment is present then one of the following is required: Name, Phone Number, or Email.</p>						
PER03	365	Communication Number Qualifier	X	ID	2/2	Used
<p>Description: Code identifying the type of communication number</p> <p>CodeList Summary (Total Codes: 42, Included: 2)</p> <p>Code Name</p> <p>EM Electronic Mail</p> <p>TE Telephone</p>						
PER04	364	Communication Number	C	AN	1/256	Used
<p>Description: Complete communications number including country or area code when applicable</p> <p>User Note 1: If PER segment is present then one of the following is required: Name, Phone Number, or Email.</p>						
PER05	365	Communication Number Qualifier	X	ID	2/2	Used
<p>Description: Code identifying the type of communication number</p> <p>CodeList Summary (Total Codes: 42, Included: 2)</p> <p>Code Name</p> <p>EM Electronic Mail</p> <p>TE Telephone</p>						
PER06	364	Communication Number	X	AN	1/256	Used
<p>Description: Complete communications number including country or area code when applicable</p>						

Syntax Rules:

1. P0304 - If either PER03 or PER04 is present, then the other is required.

2. P0506 - If either PER05 or PER06 is present, then the other is required.
3. P0708 - If either PER07 or PER08 is present, then the other is required.

FOB F.O.B. Related Instructions

Pos: 0800	Max: 1
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

Purpose: To specify transportation instructions relating to shipment

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
FOB01	146	Shipment Method of Payment	M	ID	2/2	Must use

Description: Code identifying payment terms for transportation charges

CodeList Summary (Total Codes: 31, Included: 4)

Code Name

- CC Collect
- DF Defined by Buyer and Seller
- PP Prepaid (by Seller)
- TP Third Party Pay

FOB02	309	Location Qualifier	O	ID	1/2	Used
-------	-----	--------------------	---	----	-----	------

Description: Code identifying type of location

CodeList Summary (Total Codes: 184, Included: 2)

Code Name

- DE Destination (Shipping)
- OR Origin (Shipping Point)

Syntax Rules:

1. C0302 - If FOB03 is present, then FOB02 is required.
2. C0405 - If FOB04 is present, then FOB05 is required.
3. C0706 - If FOB07 is present, then FOB06 is required.
4. C0809 - If FOB08 is present, then FOB09 is required.

Semantics:

1. FOB01 indicates which party will pay the carrier.
2. FOB02 is the code specifying transportation responsibility location.
3. FOB06 is the code specifying the title passage location.
4. FOB08 is the code specifying the point at which the risk of loss transfers. This may be different than the location specified in FOB02/FOB03 and FOB06/FOB07.

DTM Date/Time Reference

Pos: 1500	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use

Description: Code specifying type of date or time, or both date and time

CodeList Summary (Total Codes: 1280, Included: 1)

Code Name

068 Current Schedule Ship

DTM02	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

TD5 Carrier Details (Routing Sequence/Transit Time)

Pos: 2400	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 1

User Option (Usage): Must use

Purpose: To specify the carrier and sequence of routing and provide transit time information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
TD505	387	Routing	M	AN	1/35	Must use

Description: Free-form description of the routing or requested routing for shipment, or the originating carrier's identity

Syntax Rules:

1. R0204050612 - At least one of TD502, TD504, TD505, TD506 or TD512 is required.
2. C0203 - If TD502 is present, then TD503 is required.
3. C0708 - If TD507 is present, then TD508 is required.
4. C1011 - If TD510 is present, then TD511 is required.
5. C1312 - If TD513 is present, then TD512 is required.
6. C1413 - If TD514 is present, then TD513 is required.
7. C1512 - If TD515 is present, then TD512 is required.

Semantics:

1. TD515 is the country where the service is to be performed.

Comments:

1. When specifying a routing sequence to be used for the shipment movement in lieu of specifying each carrier within the movement, use TD502 to identify the party responsible for defining the routing sequence, and use TD503 to identify the actual routing sequence, specified by the party identified in TD502.

Loop Extended Reference Information

Pos: 2800	Repeat: 10
Optional	
Loop: N9	Elements: N/A

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2800	N9	Extended Reference Information	M	1		Must use
2900	MTX	Text	M	1		Must use

User Note 1:

If PO is rejected or changed, a note indicating why is required.

N9 Extended Reference Information

Pos: 2800	Max: 1
Heading - Mandatory	
Loop: N9	Elements: 2

User Option (Usage): Must use

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1731, Included: 1)

Code Name

L1 Letters or Notes

N902	127	Reference Identification	M	AN	1/50	Must use
------	-----	--------------------------	---	----	------	----------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

User Note 1: GEN: General Note

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

MTX Text

Pos: 2900	Max: 1
Heading - Mandatory	
Loop: N9	Elements: 1

User Option (Usage): Must use

Purpose: To specify textual data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MTX02	1551	Textual Data	M	AN	1/4096	Must use

Description: To transmit large volumes of message text

Syntax Rules:

1. C0102 - If MTX01 is present, then MTX02 is required.
2. C0302 - If MTX03 is present, then MTX02 is required.
3. C0504 - If MTX05 is present, then MTX04 is required.

Semantics:

1. MTX05 is the number of lines to advance before printing.

Comments:

1. If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Loop Party Identification

Pos: 3000	Repeat: 2
Mandatory	
Loop: N1	Elements: N/A

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
3000	N1	Party Identification	M	1		Must use
3100	N2	Additional Name Information	O	1		Used
3200	N3	Party Location	M	1		Must use
3300	N4	Geographic Location	M	1		Must use
3500	PER	Administrative Communications Contact	O	1		Used

N1 Party Identification

Pos: 3000	Max: 1
Heading - Mandatory	
Loop: N1	Elements: 4

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

CodeList Summary (Total Codes: 1500, Included: 2)

Code Name

BT	Bill-to-Party
ST	Ship To

User Note 1:

Mandatory

N102	93	Name	C	AN	1/60	Used
------	----	-------------	---	----	------	------

Description: Free-form name

User Note 1: *Either N102 or N104 is required.*

N103	66	Identification Code Qualifier	X	ID	1/2	Used
------	----	--------------------------------------	---	----	-----	------

Description: Code designating the system/method of code structure used for Identification Code (67)

CodeList Summary (Total Codes: 241, Included: 1)

Code Name

9	D-U-N-S+4, D-U-N-S Number with Four Character Suffix
---	--

N104	67	Identification Code	C	AN	2/80	Used
------	----	----------------------------	---	----	------	------

Description: Code identifying a party or other code

User Note 1: *Either N102 or N104 is required.*

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N2 Additional Name Information

Pos: 3100	Max: 1
Heading - Optional	
Loop: N1	Elements: 1

User Option (Usage): Used

Purpose: To specify additional names

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N201	93	Name	M	AN	1/60	Must use

Description: Free-form name

N3 Party Location

Pos: 3200	Max: 1
Heading - Mandatory	
Loop: N1	Elements: 2

User Option (Usage): Must use

Purpose: To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/55	Must use
		Description: Address information				
N302	166	Address Information	O	AN	1/55	Used
		Description: Address information				

N4 Geographic Location

Pos: 3300	Max: 1
Heading - Mandatory	
Loop: N1	Elements: 4

User Option (Usage): Must use

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	M	AN	2/30	Must use
		Description: Free-form text for city name				
N402	156	State or Province Code	C	ID	2/2	Used
		Description: Code (Standard State/Province) as defined by appropriate government agency				
		User Note 1: Required if address is within the U.S. or Canada				
N403	116	Postal Code	M	ID	3/15	Must use
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				
N404	26	Country Code	O	ID	2/3	Used
		Description: Code identifying the country				

Syntax Rules:

1. E0207 - Only one of N402 or N407 may be present.
2. C0605 - If N406 is present, then N405 is required.
3. C0704 - If N407 is present, then N404 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

PER Administrative Communications Contact

Pos: 3500	Max: 1
Heading - Optional	
Loop: N1	Elements: 5

User Option (Usage): Used

Purpose: To identify a person or office to whom administrative communications should be directed

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PER01	366	Contact Function Code	M	ID	2/2	Must use
<p>Description: Code identifying the major duty or responsibility of the person or group named</p> <p>CodeList Summary (Total Codes: 238, Included: 1)</p> <p><u>Code</u> <u>Name</u></p> <p>OC Order Contact</p>						
PER03	365	Communication Number Qualifier	X	ID	2/2	Used
<p>Description: Code identifying the type of communication number</p> <p>CodeList Summary (Total Codes: 42, Included: 2)</p> <p><u>Code</u> <u>Name</u></p> <p>EM Electronic Mail</p> <p>TE Telephone</p>						
PER04	364	Communication Number	X	AN	1/256	Used
<p>Description: Complete communications number including country or area code when applicable</p>						
PER05	365	Communication Number Qualifier	X	ID	2/2	Used
<p>Description: Code identifying the type of communication number</p> <p>CodeList Summary (Total Codes: 42, Included: 2)</p> <p><u>Code</u> <u>Name</u></p> <p>EM Electronic Mail</p> <p>TE Telephone</p>						
PER06	364	Communication Number	X	AN	1/256	Used
<p>Description: Complete communications number including country or area code when applicable</p>						

Syntax Rules:

1. P0304 - If either PER03 or PER04 is present, then the other is required.
2. P0506 - If either PER05 or PER06 is present, then the other is required.
3. P0708 - If either PER07 or PER08 is present, then the other is required.

Loop Baseline Item Data

Pos: 0100	Repeat: 100000
Mandatory	
Loop: PO1	Elements: N/A

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	PO1	Baseline Item Data	M	1		Must use
0500		Loop PID	M		1	Must use
2700		Loop ACK	M		5	Must use
3500		Loop N9	O		10	Used

PO1 Baseline Item Data

Pos: 0100	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 12

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	Assigned Identification	O	AN	1/20	Used
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
PO102	380	Quantity	M	R	1/15	Must use
		Description: Numeric value of quantity				
		User Note 1: <i>Original order Qty Must be a whole number (no decimal)</i>				
PO103	355	Unit or Basis for Measurement Code	M	ID	2/2	Must use
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				

CodeList Summary (Total Codes: 844, Included: 30)

<u>Code</u>	<u>Name</u>
03	Seconds
BD	Bundle
BG	Bag
BO	Bottle
BX	Box
CA	Case
CN	Can
CT	Carton
DZ	Dozen
EA	Each
FT	Foot
GA	Gallon
GS	Gross
HD	Half Dozen
IN	Inch
KT	Kit
LB	Pound
LO	Lot
PC	Piece
PD	Pad
PK	Package
PR	Pair
RL	Roll
SF	Square Foot
SH	Sheet
SL	Sleeve

Code Name

ST Set
 TB Tube
 TH Thousand
 UN Unit

PO104 212 **Unit Price** X R 1/17 Used

Description: Price per unit of product, service, commodity, etc.

User Note 1: *If ACK01 = IP, updated price should be sent in PO104.*

PO106 235 **Product/Service ID Qualifier** M ID 2/2 Must use

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 519, Included: 2)

Code Name

IN Buyer's Item Number
 VN Vendor's (Seller's) Item Number

PO107 234 **Product/Service ID** M AN 1/48 Must use

Description: Identifying number for a product or service

PO108 235 **Product/Service ID Qualifier** M ID 2/2 Must use

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 519, Included: 2)

Code Name

IN Buyer's Item Number
 VN Vendor's (Seller's) Item Number

PO109 234 **Product/Service ID** M AN 1/48 Must use

Description: Identifying number for a product or service

PO110 235 **Product/Service ID Qualifier** X ID 2/2 Used

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 519, Included: 3)

Code Name

EN EAN/UCC - 13
 UK GTIN 14-digit Data Structure
 UP UCC - 12

PO111 234 **Product/Service ID** X AN 1/48 Used

Description: Identifying number for a product or service

PO112 235 **Product/Service ID Qualifier** X ID 2/2 Used

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 519, Included: 3)

Code Name

EN EAN/UCC - 13
 UK GTIN 14-digit Data Structure
 UP UCC - 12

PO113 234 **Product/Service ID** X AN 1/48 Used

Description: Identifying number for a product or service

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Semantics:

1. PO102 is quantity ordered.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Loop Product/Item Description

Pos: 0500	Repeat: 1
Mandatory	
Loop: PID	Elements: N/A

User Option (Usage): Must use

Purpose: To describe a product or process in coded or free-form format

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0500	PID	Product/Item Description	M	1		Must use

PID Product/Item Description

Pos: 0500	Max: 1
Detail - Mandatory	
Loop: PID	Elements: 3

User Option (Usage): Must use

Purpose: To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID01	349	Item Description Type	M	ID	1/1	Must use

Description: Code indicating the format of a description

CodeList Summary (Total Codes: 3, Included: 1)

Code Name

F Free-form

PID02	750	Product/Process Characteristic Code	M	ID	2/3	Must use
-------	-----	-------------------------------------	---	----	-----	----------

Description: Code identifying the general class of a product or process characteristic

CodeList Summary (Total Codes: 238, Included: 1)

Code Name

08 Product

PID05	352	Description	M	AN	1/80	Must use
-------	-----	-------------	---	----	------	----------

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.
3. PID07 specifies the individual code list of the agency specified in PID03.

Loop Line Item Acknowledgment

Pos: 2700	Repeat: 5
Mandatory	
Loop: ACK	Elements: N/A

User Option (Usage): Must use

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2700	ACK	Line Item Acknowledgment	M	1		Must use

ACK Line Item Acknowledgment

Pos: 2700 Max: 1
 Detail - Mandatory
 Loop: ACK Elements: 5

User Option (Usage): Must use

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ACK01	668	Line Item Status Code	M	ID	2/2	Must use

Description: Code specifying the action taken by the seller on a line item requested by the buyer

CodeList Summary (Total Codes: 26, Included: 7)

Code Name

- DR Item Accepted - Date Rescheduled
- IA Item Accepted
- IB Item Backordered
- IC Item Accepted - Changes Made
- IP Item Accepted - Price Changed
- IQ Item Accepted - Quantity Changed
- IR Item Rejected

ACK02	380	Quantity	C	R	1/15	Used
-------	-----	----------	---	---	------	------

Description: Numeric value of quantity

User Note 1: Required if ACK01 = IB or IQ
 Must be a whole number (no decimal)

ACK03	355	Unit or Basis for Measurement Code	C	ID	2/2	Used
-------	-----	------------------------------------	---	----	-----	------

Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken

User Note 1: Required if ACK01 = IB or IQ

CodeList Summary (Total Codes: 844, Included: 30)

Code Name

- 03 Seconds
- BD Bundle
- BG Bag
- BO Bottle
- BX Box
- CA Case
- CN Can
- CT Carton
- DZ Dozen
- EA Each
- FT Foot
- GA Gallon
- GS Gross
- HD Half Dozen

conjunction with ACK01 to further clarify the status.

Loop Extended Reference Information

Pos: 3500	Repeat: 10
Optional	
Loop: N9	Elements: N/A

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
3500	N9	Extended Reference Information	M	1		Must use
3600	MTX	Text	M	1		Must use

N9 Extended Reference Information

Pos: 3500	Max: 1
Detail - Mandatory	
Loop: N9	Elements: 2

User Option (Usage): Must use

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1731, Included: 1)

Code Name

L1 Letters or Notes

N902	127	Reference Identification	M	AN	1/50	Must use
------	-----	--------------------------	---	----	------	----------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

User Note 1: GEN: General Note

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

User Note 1:

If a Line Item is rejected or changed, a note indictating why is required.

MTX Text

Pos: 3600	Max: 1
Detail - Mandatory	
Loop: N9	Elements: 1

User Option (Usage): Must use
Purpose: To specify textual data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MTX02	1551	Textual Data	M	AN	1/4096	Must use

Description: To transmit large volumes of message text

Syntax Rules:

1. C0102 - If MTX01 is present, then MTX02 is required.
2. C0302 - If MTX03 is present, then MTX02 is required.
3. C0504 - If MTX05 is present, then MTX04 is required.

Semantics:

1. MTX05 is the number of lines to advance before printing.

Comments:

1. If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

SE Transaction Set Trailer

Pos: 0300	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	N0	1/10	Must use
		Description: Total number of segments included in a transaction set including ST and SE segments				
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

Comments:

1. SE is the last segment of each transaction set.