

EDI Guideline

X12/V4010/855 : 855 Purchase Order Acknowledgment

Version: 2.4

Author:	InterTrade
Publication:	3/25/2023
Trading Partner:	Quebec EDI Healthcare Program

Document Change Log

Version	Date	Page	Description
2.1	03/22/2021	8	BAK08 Added
2.1	03/22/2021	21, 26, 28 & 32	BAK09 Added
2.1	03/22/2021	31	Updated Sample 855
2.2	05/05/2021	29	N9 Added
2.2	05/05/2021	30	MSG Added
2.2	05/05/2021	36	Updated Sample 855
2.3	08/15/2022	27	N9 Correction removed position N907
2.4	03/25/2023	19	Remove reference to specific UoM
2.4	03/25/2023	23	Remove reference to specific UoM
2.4	03/25/2023	23	Update Acceptable ACK01 codes

Table of Contents

Purchase Order Acknowledgment	1
Interchange Control Header	3
Functional Group Header	5
Transaction Set Header	7
Beginning Segment for Purchase Order Acknowledgment	8
Date/Time Reference	9
Loop Reference Identification	10
Reference Identification	11
Message Text	12
Loop Name	13
Name	14
Additional Name Information	15
Address Information	16
Geographic Location	17
Loop Baseline Item Data	18
Baseline Item Data	19
Loop Product/Item Description	20
Product/Item Description	21
Loop Line Item Acknowledgment	22
Line Item Acknowledgment	23
Loop Reference Identification	25
Reference Identification	26
Message Text	27
Loop Transaction Totals	28
Transaction Totals	29
Transaction Set Trailer	30
Functional Group Trailer	31
Interchange Control Trailer	32
Sample 855:	33

855

Purchase Order Acknowledgment

Functional Group=PR

Purpose: This Draft Standard for Trial Use contains the format and establishes the data contents of the Purchase Order Acknowledgment Transaction Set (855) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to a seller's acknowledgment of a buyer's purchase order. This transaction set can also be used as notification of a vendor generated order. This usage advises a buyer that a vendor has or will ship merchandise as prearranged in their partnership.

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	ST	Transaction Set Header	M	1			Must use
020	BAK	Beginning Segment for Purchase Order Acknowledgment	M	1			Must use
150	DTM	Date/Time Reference	M	10			Must use
<u>LOOP ID - N9</u>					<u>1000</u>		
280	N9	Reference Identification	O	1			Used
290	MSG	Message Text	O	1000			Used
<u>LOOP ID - N1</u>					<u>3</u>		
300	N1	Name	M	1			Must use
310	N2	Additional Name Information	O	2			Used
320	N3	Address Information	O	2			Used
330	N4	Geographic Location	O	1			Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<u>LOOP ID - PO1</u>					<u>100000</u>	<u>N2/010L</u>	
010	PO1	Baseline Item Data	M	1		N2/010	Must use
<u>LOOP ID - PID</u>					<u>1000</u>		
050	PID	Product/Item Description	O	1			Used
<u>LOOP ID - ACK</u>					<u>104</u>		
270	ACK	Line Item Acknowledgment	M	1			Must use
<u>LOOP ID - N9</u>					<u>1000</u>		
350	N9	Reference Identification	O	1			Used
360	MSG	Message Text	O	1000			Used

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<u>LOOP ID - CTT</u>					<u>1</u>	<u>N3/010L</u>	
010	CTT	Transaction Totals	M	1		N3/010	Must use
030	SE	Transaction Set Trailer	M	1			Must use

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	GE	Functional Group Trailer	M	1			Must use

IEA Interchange Control Trailer M 1 Must use

Notes:

2/010L PO102 is required.

2/010 PO102 is required.

3/010L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

3/010 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

User Option (Usage): Must use

Purpose: To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	Authorization Information Qualifier	M	ID	2/2	Must use
		Description: Code to identify the type of information in the Authorization Information All valid standard codes are used. (Total Codes: 7)				
ISA02	I02	Authorization Information	M	AN	10/10	Must use
		Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)				
ISA03	I03	Security Information Qualifier	M	ID	2/2	Must use
		Description: Code to identify the type of information in the Security Information All valid standard codes are used. (Total Codes: 2)				
ISA04	I04	Security Information	M	AN	10/10	Must use
		Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)				
ISA05	I05	Interchange ID Qualifier	M	ID	2/2	Must use
		Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified All valid standard codes are used. (Total Codes: 38)				
ISA06	I06	Interchange Sender ID	M	AN	15/15	Must use
		Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element				
ISA07	I05	Interchange ID Qualifier	M	ID	2/2	Must use
		Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified All valid standard codes are used. (Total Codes: 38)				
ISA08	I07	Interchange Receiver ID	M	AN	15/15	Must use
		Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them				
ISA09	I08	Interchange Date	M	DT	6/6	Must use
		Description: Date of the interchange				
ISA10	I09	Interchange Time	M	TM	4/4	Must use
		Description: Time of the interchange				
ISA11	I10	Interchange Control Standards Identifier	M	ID	1/1	Must use
		Description: Code to identify the agency responsible for the control standard used by the message that is enclosed by the interchange header and trailer All valid standard codes are used. (Total Codes: 1)				

ISA12	I11	Interchange Control Version Number	M	ID	5/5	Must use
Description: Code specifying the version number of the interchange control segments						
Code List Summary (Total Codes: 14, Included: 1)						
		<u>Code</u>	<u>Name</u>			
		00401	Draft Standards for Trial Use Approved for Publication by ASC X12 Procedures Review Board through October 1997			
ISA13	I12	Interchange Control Number	M	N0	9/9	Must use
Description: A control number assigned by the interchange sender						
ISA14	I13	Acknowledgment Requested	M	ID	1/1	Must use
Description: Code sent by the sender to request an interchange acknowledgment (TA1)						
All valid standard codes are used. (Total Codes: 2)						
ISA15	I14	Usage Indicator	M	ID	1/1	Must use
Description: Code to indicate whether data enclosed by this interchange envelope is test, production or information						
All valid standard codes are used. (Total Codes: 3)						
ISA16	I15	Component Element Separator	M		1/1	Must use
Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator						

GS**Functional Group Header**

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

User Option (Usage): Must use**Purpose:** To indicate the beginning of a functional group and to provide control information**Element Summary:**

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS01	479	Functional Identifier Code	M	ID	2/2	Must use
Description: Code identifying a group of application related transaction sets						
Code List Summary (Total Codes: 240, Included: 1)						
		<u>Code</u>		<u>Name</u>		
		PR		Purchase Order Acknowledgement (855)		
GS02	142	Application Sender's Code	M	AN	2/15	Must use
Description: Code identifying party sending transmission; codes agreed to by trading partners						
GS03	124	Application Receiver's Code	M	AN	2/15	Must use
Description: Code identifying party receiving transmission; codes agreed to by trading partners						
GS04	373	Date	M	DT	8/8	Must use
Description: Date expressed as CCYYMMDD						
GS05	337	Time	M	TM	4/8	Must use
Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)						
GS06	28	Group Control Number	M	N0	1/9	Must use
Description: Assigned number originated and maintained by the sender						
GS07	455	Responsible Agency Code	M	ID	1/2	Must use
Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480						
All valid standard codes are used. (Total Codes: 2)						
GS08	480	Version / Release / Industry Identifier Code	M	AN	1/12	Must use
Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed						
Code List Summary (Total Codes: 39, Included: 1)						
		<u>Code</u>		<u>Name</u>		
		004010		Draft Standards Approved for Publication by ASC X12 Procedures Review Board through October 1997		

Semantics:

1. GS04 is the group date.
2. GS05 is the group time.

3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

ST Transaction Set Header

Pos: 010	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use
Description: Code uniquely identifying a Transaction Set						
Code List Summary (Total Codes: 298, Included: 1)						
		<u>Code</u>		<u>Name</u>		
		855		Purchase Order Acknowledgment		
ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set						

Semantics:

1. The transaction set identifier (ST01) used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).

BAK Beginning Segment for Purchase Order Acknowledgment

Pos: 020 Max: 1
 Heading - Mandatory
 Loop: N/A Elements: 7

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Acknowledgment Transaction Set and transmit identifying numbers and dates

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
BAK01	353	Transaction Set Purpose Code	M	ID	2/2	Must use
Description: Code identifying purpose of transaction set						
Code List Summary (Total Codes: 65, Included: 1)						
		Code	Name			
		06	Confirmation			
BAK02	587	Acknowledgment Type	M	ID	2/2	Must use
Description: Code specifying the type of acknowledgment						
Code List Summary (Total Codes: 15, Included: 5)						
		Code	Name			
		AC	Acknowledge - With Detail and Change			
		AD	Acknowledge - With Detail, No Change			
		AE	Acknowledge - With Exception Detail Only			
		AT	Accepted			
		RD	Reject with Detail			
BAK03	324	Purchase Order Number	M	AN	1/22	Must use
Description: Identifying number for Purchase Order assigned by the orderer/purchaser						
BAK04	373	Date	M	DT	8/8	Must use
Description: Date expressed as CCYYMMDD						
BAK05	328	Release Number	O	AN	1/30	Used
Description: Number identifying a release against a Purchase Order previously placed by the parties involved in the transaction						
BAK08	127	Reference Identification	O	AN	1/30	Used
Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier						
User Note 1: Supplier's Order Number						
BAK09	373	Date	O	DT	8/8	Used
Description: Date expressed as CCYYMMDD						
User Note 1: Supplier order Date						

Semantics:

1. BAK04 is the date assigned by the purchaser to purchase order.

DTM Date/Time Reference

Pos: 150	Max: 10
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To specify pertinent dates and times

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use

Description: Code specifying type of date or time, or both date and time

Code List Summary (Total Codes: 1112, Included: 4)

Code	Name
002	Delivery Requested
010	Requested Ship
017	Estimated Delivery
069	Promised for Delivery

DTM02	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.

Loop Reference Identification

Pos: 280	Repeat: 1000
Optional	
Loop: N9	Elements: N/A

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
280	N9	Reference Identification	O	1		Used
290	MSG	Message Text	O	1000		Used

N9**Reference Identification**

Pos: 280	Max: 1
Heading - Optional	
Loop: N9	Elements: 2

User Option (Usage): Used**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier**Element Summary:**

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification**Code List Summary** (Total Codes: 1503, Included: 1)

<u>Code</u>	<u>Name</u>
ZZ	Mutually Defined

N902	127	Reference Identification	X	AN	1/30	Used
------	-----	--------------------------	---	----	------	------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier**Syntax Rules:**

1. R0203 - At least one of N902 or N903 is required.

MSG Message Text

Pos: 290	Max: 1000
Heading - Optional	
Loop: N9	Elements: 1

User Option (Usage): Used

Purpose: To provide a free-form format that allows the transmission of text information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MSG01	933	Free-Form Message Text	M	AN	1/264	Must use

Description: Free-form message text

Loop Name

Pos: 300	Repeat: 3
Mandatory	
Loop: N1	Elements: N/A

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
300	N1	Name	M	1		Must use
310	N2	Additional Name Information	O	2		Used
320	N3	Address Information	O	2		Used
330	N4	Geographic Location	O	1		Used

N1 Name

Pos: 300	Max: 1
Heading - Mandatory	
Loop: N1	Elements: 4

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use
Description: Code identifying an organizational entity, a physical location, property or an individual						
Code List Summary (Total Codes: 1312, Included: 3)						
		<u>Code</u>		<u>Name</u>		
		BT		Bill-to-Party		
		ST		Ship To		
		VN		Vendor		
N102	93	Name	X	AN	1/60	Used
Description: Free-form name						
N103	66	Identification Code Qualifier	X	ID	1/2	Used
Description: Code designating the system/method of code structure used for Identification Code (67)						
Code List Summary (Total Codes: 215, Included: 3)						
		<u>Code</u>		<u>Name</u>		
		91		Assigned by Seller or Seller's Agent		
		92		Assigned by Buyer or Buyer's Agent		
		ZZ		Mutually Defined		
N104	67	Identification Code	X	AN	2/80	Used
Description: Code identifying a party or other code						

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.

N2**Additional Name
Information**

Pos: 310	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used**Purpose:** To specify additional names or those longer than 35 characters in length**Element Summary:**

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N201	93	Name	O	AN	1/60	Used
		Description: Free-form name				
N202	93	Name	O	AN	1/60	Used
		Description: Free-form name				

N3 Address Information

Pos: 320	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used

Purpose: To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	O	AN	1/55	Used
		Description: Address information				
N302	166	Address Information	O	AN	1/55	Used
		Description: Address information				

N4 Geographic Location

Pos: 330	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

User Option (Usage): Used

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Used
		Description: Free-form text for city name				
N402	156	State or Province Code	O	ID	2/2	Used
		Description: Code (Standard State/Province) as defined by appropriate government agency				
N403	116	Postal Code	O	ID	3/15	Used
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				
N404	26	Country Code	O	ID	2/3	Used
		Description: Code identifying the country				

Syntax Rules:

1. C0605 - If N406 is present, then N405 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

Loop Baseline Item Data

Pos: 010 Repeat: 100000
Mandatory
Loop: PO1 Elements: N/A

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
010	PO1	Baseline Item Data	M	1		Must use
050		Loop PID	O		1000	Used
270		Loop ACK	M		104	Must use
350		Loop N9	O		1000	Used

PO1 Baseline Item Data

Pos: 010	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 8

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	Assigned Identification	M	AN	1/20	Must use
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
PO102	330	Quantity Ordered	M	R	1/15	Must use
		Description: Quantity ordered				
PO103	355	Unit or Basis for Measurement Code	M	ID	2/2	Must use
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		User Note 1: as per contract agreement				
PO104	212	Unit Price	M	R	1/17	Must use
		Description: Price per unit of product, service, commodity, etc.				
PO106	235	Product/Service ID Qualifier	M	ID	2/2	Must use
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		Code List Summary (Total Codes: 477, Included: 2)				
		<u>Code</u>	<u>Name</u>			
		VC	Vendor's (Seller's) Catalog Number			
		VN	Vendor's (Seller's) Item Number			
PO107	234	Product/Service ID	M	AN	1/48	Must use
		Description: Identifying number for a product or service				
PO108	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		Code List Summary (Total Codes: 477, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		IN	Buyer's Item Number			
PO109	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Loop Product/Item Description

Pos: 050	Repeat: 1000
	Optional
Loop: PID	Elements: N/A

User Option (Usage): Used

Purpose: To describe a product or process in coded or free-form format

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
050	PID	Product/Item Description	O	1		Used

PID Product/Item Description

Pos: 050	Max: 1
Detail - Optional	
Loop: PID	Elements: 2

User Option (Usage): Used

Purpose: To describe a product or process in coded or free-form format

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
PID01	349	Item Description Type	O	ID	1/1	Used

Description: Code indicating the format of a description

Code List Summary (Total Codes: 3, Included: 1)

Code	Name
F	Free-form

PID05	352	Description	X	AN	1/80	Used
-------	-----	-------------	---	----	------	------

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.

Loop Line Item Acknowledgment

Pos: 270	Repeat: 104
Mandatory	
Loop: ACK	Elements: N/A

User Option (Usage): Must use

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
270	ACK	Line Item Acknowledgment	M	1		Must use

ACK Line Item Acknowledgment

Pos: 270	Max: 1
Detail - Mandatory	
Loop: ACK	Elements: 10

User Option (Usage): Must use

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
ACK01	668	Line Item Status Code	M	ID	2/2	Must use

Description: Code specifying the action taken by the seller on a line item requested by the buyer

Code List Summary (Total Codes: 26, Included: 12)

Code	Name
AC	Item Accepted and Shipped
AR	Item Accepted and Released for Shipment
BP	Item Accepted - Partial Shipment, Balance Backordered
IA	Item Accepted
IB	Item Backordered
IC	Item Accepted - Changes Made
ID	Item Deleted
IP	Item Accepted - Price Changed
IQ	Item Accepted - Quantity Changed
IR	Item Rejected
IS	Item Accepted - Substitution Made
R2	Item Rejected, Invalid Item Product Number

ACK02	380	Quantity	M	R	1/15	Must use
-------	-----	----------	---	---	------	----------

Description: Numeric value of quantity

ACK03	355	Unit or Basis for Measurement Code	M	ID	2/2	Must use
-------	-----	------------------------------------	---	----	-----	----------

Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken

User Note 1: *as per contract agreement*

ACK04	374	Date/Time Qualifier	C	ID	3/3	Used
-------	-----	---------------------	---	----	-----	------

Description: Code specifying type of date or time, or both date and time

User Note 1: *Estimated Delivery date required for backorders*

Code List Summary (Total Codes: 1112, Included: 2)

Code	Name
017	Estimated Delivery
068	Current Schedule Ship

ACK05	373	Date	X	DT	8/8	Used
-------	-----	------	---	----	-----	------

Description: Date expressed as CCYYMMDD

ACK07	235	Product/Service ID Qualifier	M	ID	2/2	Must use
-------	-----	------------------------------	---	----	-----	----------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

Code List Summary (Total Codes: 477, Included: 2)

Code	Name
VC	Vendor's (Seller's) Catalog Number
VN	Vendor's (Seller's) Item Number

ACK08	234	Product/Service ID	M	AN	1/48	Must use
-------	-----	--------------------	---	----	------	----------

		Description: Identifying number for a product or service				
ACK09	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		Code List Summary (Total Codes: 477, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		IN	Buyer's Item Number			
ACK10	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				
ACK15	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		All valid standard codes are used. (Total Codes: 477)				

Syntax Rules:

1. P0203 - If either ACK02 or ACK03 is present, then the other is required.
2. C0405 - If ACK04 is present, then ACK05 is required.
3. P0708 - If either ACK07 or ACK08 is present, then the other is required.
4. P0910 - If either ACK09 or ACK10 is present, then the other is required.

Semantics:

1. ACK29 Industry Reason Code may be used to identify the item status. In addition, it may be used in conjunction with ACK01 to further clarify the status.

Loop Reference Identification

Pos: 350	Repeat: 1000
	Optional
Loop: N9	Elements: N/A

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
350	N9	Reference Identification	O	1		Used
360	MSG	Message Text	O	1000		Used

N9**Reference Identification**

Pos: 350	Max: 1
Detail - Optional	
Loop: N9	Elements: 2

User Option (Usage): Used**Purpose:** To transmit identifying information as specified by the Reference Identification Qualifier**Element Summary:**

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification**Code List Summary** (Total Codes: 1503, Included: 1)

<u>Code</u>	<u>Name</u>
ZZ	Mutually Defined

N902	127	Reference Identification	X	AN	1/30	Used
------	-----	--------------------------	---	----	------	------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier**Semantics:**

1.

MSG Message Text

Pos: 360	Max: 1000
Detail - Optional	
Loop: N9	Elements: 1

User Option (Usage): Used

Purpose: To provide a free-form format that allows the transmission of text information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MSG01	933	Free-Form Message Text	M	AN	1/264	Must use

Description: Free-form message text

Syntax Rules:

1. C0302 - If MSG03 is present, then MSG02 is required.

Semantics:

1. MSG03 is the number of lines to advance before printing.

Comments:

1. MSG02 is not related to the specific characteristics of a printer, but identifies top of page, advance a line, etc.
2. If MSG02 is "AA - Advance the specified number of lines before print" then MSG03 is required.

Loop Transaction Totals

Pos: 010	Repeat: 1
Mandatory	
Loop: CTT	Elements: N/A

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
010	CTT	Transaction Totals	M	1		Must use

CTT Transaction Totals

Pos: 010	Max: 1
Summary - Mandatory	
Loop: CTT	Elements: 1

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use

Description: Total number of line items in the transaction set

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

SE Transaction Set Trailer

Pos: 030	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	N0	1/10	Must use
Description: Total number of segments included in a transaction set including ST and SE segments						
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set						

Comments:

1. SE is the last segment of each transaction set.

GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	Number of Transaction Sets Included	M	N0	1/6	Must use
Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element						
GE02	28	Group Control Number	M	N0	1/9	Must use
Description: Assigned number originated and maintained by the sender						

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	Number of Included Functional Groups	M	N0	1/5	Must use
Description: A count of the number of functional groups included in an interchange						
IEA02	I12	Interchange Control Number	M	N0	9/9	Must use
Description: A control number assigned by the interchange sender						

Sample 855:

ISA*00* *00* *ZZ*SUPPLIER *ZZ*HOSPITAL *150120*1204*U*00401*000014609*0*P*|~
GS*PR*SUPPLIER*HOSPITAL*20150120*1204*14609*X*004010~
ST*855*146090004~
BAK*06*AC*999999-D*20150120****36538175*20150120~
DTM*010*20150120~
N1*ST*HOSPITAL SHIP TO*91*99999~
N1*BT*HOSPITAL BILL TO*91*99999-99999~
N1*VN*SUPPLIER INFO*91*12345~
PO1*1*1*CA*13.16**VC*AB1234*IN*90-9-07676876~
PID*F****PRODUCT DESCRIPTION 1~
ACK*IA*1*CA*068*20210402**VC*AB1234*IN*90-9-07676876~
PO1*2*2*CA*50.25**VC*999999*IN*6567689-987~
PID*F****PRODUCT DESCRIPTION 2~
ACK*IB*2*CA*017*20210622**VC*999999*IN*6567689-987~
N9*ZZ*COMMENTS~
MSG*ITEM LEVEL COMMENT 1~
MSG*ITEM LEVEL COMMENT 2~
PO1*3*1*CA*45**VC*123456CD*IN*65646578-5456~
PID*F****PRODUCT DESCRIPTION 3~
ACK*IA*1*CA*068*20210402**VC*123456CD*IN*65646578-5456~
CTT*3~
SE*20*146090004~
GE*1*14609~
IEA*1*000014609~