

850 Purchase Order

X12/V4030/850 : 850 Purchase Order

Version: 1.0 Draft

Author:	Dollar Tree Stores
Company:	Dollar Tree Stores
Publication:	12/21/2021
Notes:	

Table of Contents

850 Purchase Order	1
ISA Interchange Control Header	3
GS Functional Group Header	7
ST Transaction Set Header	9
BEG Beginning Segment for Purchase Order	10
REF Reference Identification	11
REF Reference Identification	12
REF Reference Identification	13
PER Administrative Communications Contact	14
FOB F.O.B. Related Instructions	15
ITD Terms of Sale/Deferred Terms of Sale	16
DTM Date/Time Reference	17
DTM Date/Time Reference	18
DTM Date/Time Reference	19
DTM Date/Time Reference	20
TD5 Carrier Details (Routing Sequence/Transit Time)	21
N1 Name	22
N3 Address Information	23
N4 Geographic Location	24
N1 Name	25
N3 Address Information	26
N4 Geographic Location	27
N1 Name	28
N3 Address Information	29
N4 Geographic Location	30
N1 Name	31
N3 Address Information	32
N4 Geographic Location	33
PO1 Baseline Item Data	34
CTP Pricing Information	36
PID Product/Item Description	37
PO4 Item Physical Details	38
CTT Transaction Totals	39
AMT Monetary Amount	40
SE Transaction Set Trailer	41
GE Functional Group Trailer	42
IEA Interchange Control Trailer	43

850 Purchase Order

Functional Group=**PO**

Purpose: This Draft Standard for Trial Use contains the format and establishes the data contents of the Purchase Order Transaction Set (850) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to the placement of purchase orders for goods and services. This transaction set should not be used to convey purchase order changes or purchase order acknowledgment information.

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
0100	ST	Transaction Set Header	M	1			Must use
0200	BEG	Beginning Segment for Purchase Order	M	1			Must use
0500	REF	Reference Identification	O	>1			Used
0500	REF	Reference Identification	O	>1			Used
0500	REF	Reference Identification	O	>1			Used
0600	PER	Administrative Communications Contact	O	3			Used
0800	FOB	F.O.B. Related Instructions	O	>1			Used
1300	ITD	Terms of Sale/Deferred Terms of Sale	O	>1			Used
1500	DTM	Date/Time Reference	O	10			Used
1500	DTM	Date/Time Reference	O	10			Used
1500	DTM	Date/Time Reference	O	10			Used
1500	DTM	Date/Time Reference	O	10			Used
2400	TD5	Carrier Details (Routing Sequence/Transit Time)	O	>1			Used

<u>LOOP ID - N1</u>					<u>200</u>		
3100	N1	Name	O	1			Used
3300	N3	Address Information	O	2			Used
3400	N4	Geographic Location	O	>1			Used

<u>LOOP ID - N1</u>					<u>200</u>		
3100	N1	Name	O	1			Used
3300	N3	Address Information	O	2			Used
3400	N4	Geographic Location	O	>1			Used

<u>LOOP ID - N1</u>					<u>200</u>		
3100	N1	Name	O	1			Used
3300	N3	Address Information	O	2			Used
3400	N4	Geographic Location	O	>1			Used

<u>LOOP ID - N1</u>					<u>200</u>		
3100	N1	Name	O	1			Used
3300	N3	Address Information	O	2			Used
3400	N4	Geographic Location	O	>1			Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - PO1					100000	N2/0100L	
0100	PO1	Baseline Item Data	M	1		N2/0100	Must use
LOOP ID - CTP					≥1		
0400	CTP	Pricing Information	O	1			Used
LOOP ID - PID					1000		
0500	PID	Product/Item Description	O	1			Used
0900	PO4	Item Physical Details	O	>1			Used

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - CTT					1	N3/0100L	
0100	CTT	Transaction Totals	O	1		N3/0100	Used
0200	AMT	Monetary Amount	O	1		N3/0200	Used
0300	SE	Transaction Set Trailer	M	1			Must use

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	GE	Functional Group Trailer	M	1			Must use
	IEA	Interchange Control Trailer	M	1			Must use

Notes:

- 2/0100L PO102 is required.
- 2/0100 PO102 is required.
- 3/0100L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.
- 3/0100 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.
- 3/0200 If AMT is used in the summary area, then AMT01 will = TT and AMT02 will indicate total transaction amount as calculated by the sender.

ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

User Option (Usage): Must use

Purpose: To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	Authorization Information Qualifier	M	ID	2/2	Must use
<p>Description: Code identifying the type of information in the Authorization Information</p> <p>Code List Summary (Total Codes: 7, Included: 1)</p> <p>Code Name</p> <p>00 No Authorization Information Present (No Meaningful Information in I02)</p>						
ISA02	I02	Authorization Information	M	AN	10/10	Must use
<p>Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)</p>						
ISA03	I03	Security Information Qualifier	M	ID	2/2	Must use
<p>Description: Code identifying the type of information in the Security Information</p> <p>Code List Summary (Total Codes: 2, Included: 1)</p> <p>Code Name</p> <p>00 No Security Information Present (No Meaningful Information in I04)</p>						
ISA04	I04	Security Information	M	AN	10/10	Must use
<p>Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)</p>						
ISA05	I05	Interchange ID Qualifier	M	ID	2/2	Must use
<p>Description: Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified</p> <p>Code List Summary (Total Codes: 41, Included: 1)</p> <p>Code Name</p> <p>ZZ Mutually Defined</p>						
ISA06	I06	Interchange Sender ID	M	AN	15/15	Must use
<p>Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element</p> <p>Notes: FAMILYDOLLAR</p>						
ISA07	I05	Interchange ID Qualifier	M	ID	2/2	Must use
<p>Description: Code indicating the system/method</p>						

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
		of code structure used to designate the sender or receiver ID element being qualified				
		Code List Summary (Total Codes: 41, Included: 41)				
		<u>Code</u>				
		<u>Name</u>				
	01	Duns (Dun & Bradstreet)				
	02	SCAC (Standard Carrier Alpha Code)				
	03	FMC (Federal Maritime Commission)				
	04	IATA (International Air Transport Association)				
	07	UCC/EAN Location Code				
	08	UCC EDI Communications ID (Comm ID)				
	09	X.121 (CCITT)				
	10	Department of Defense (DoD) Activity Address Code				
	11	DEA (Drug Enforcement Administration)				
	12	Phone (Telephone Companies)				
	13	UCS Code (The UCS Code is a Code Used for UCS Transmissions; it includes the Area Code and Telephone Number of a Modem; it Does Not Include Punctuation, Blanks or Access Code)				
	14	Duns Plus Suffix				
	15	Petroleum Accountants Society of Canada Company Code				
	16	Duns Number With 4-Character Suffix				
	17	American Bankers Association (ABA) Transit Routing Number (Including Check Digit, 9 Digit)				
	18	Association of American Railroads (AAR) Standard Distribution Code				
	19	EDI Council of Australia (EDICA) Communications ID Number (COMM ID)				
	20	Health Industry Number (HIN)				
	21	Integrated Postsecondary Education Data System, or (IPEDS)				
	22	Federal Interagency Commission on Education, or FICE				
	23	National Center for Education Statistics Common Core of Data 12-Digit Number for Pre-K-Grade 12 Institutes, or NCES				
	24	The College Board's Admission Testing Program 4-Digit Code of Postsecondary Institutes, or ATP				
	25	ACT, Inc. 4-Digit Code of Postsecondary Institutions.				
	26	Statistics of Canada List of Postsecondary Institutions				
	27	Carrier Identification Number as assigned by Health Care Financing Administration (HCFA)				
	28	Fiscal Intermediary Identification Number as assigned by Health Care Financing Administration (HCFA)				
	29	Medicare Provider and Supplier Identification Number as assigned by Health Care Financing Administration (HCFA)				
	30	U.S. Federal Tax Identification Number				
	31	Jurisdiction Identification Number Plus 4 as assigned by the International Association of Industrial Accident Boards and Commissions (IAIABC)				
	32	U.S. Federal Employer Identification Number (FEIN)				
	33	National Association of Insurance Commissioners Company Code (NAIC)				
	34	Medicaid Provider and Supplier Identification Number as assigned by individual State Medicaid Agencies in conjunction with Health Care Financing Administration (HCFA)				
	35	Statistics Canada Canadian College Student Information System Institution Codes				
	36	Statistics Canada University Student Information System Institution Codes				
	37	Society of Property Information Compilers and Analysts				
	38	The College Board and ACT, Inc. 6-Digit Code List of Secondary Institutions				
	AM	Association Mexicana del Codigo de Producto (AMECOP) Communication ID				
	NR	National Retail Merchants Association (NRMA) - Assigned				
	SA	User Identification Number as assigned by the Safety and the Fitness Electronic Records (SAFER) System				
	SN	Standard Address Number				
	ZZ	Mutually Defined				

ISA08	I07	Interchange Receiver ID	M	AN	15/15	Must use
<p>Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them</p> <p>Notes: <i>Receiver ID</i></p>						
ISA09	I08	Interchange Date	M	DT	6/6	Must use
<p>Description: Date of the interchange</p>						
ISA10	I09	Interchange Time	M	TM	4/4	Must use
<p>Description: Time of the interchange</p>						
ISA11	I65	Repetition Separator	M		1/1	Must use
<p>Description: Type is not applicable; the repetition separator is a delimiter and not a data element; this field provides the delimiter used to separate repeated occurrences of a simple data element or a composite data structure; this value must be different than the data element separator, component element separator, and the segment terminator</p> <p>Notes: <i>Family Dollar uses - : (HEX3A)</i></p>						
ISA12	I11	Interchange Control Version Number	M	ID	5/5	Must use
<p>Description: Code specifying the version number of the interchange control segments</p> <p>Code List Summary (Total Codes: 15, Included: 1)</p> <p>Code Name</p> <p>00403 Draft Standards for Trial Use Approved for Publication by ASC X12 Procedures Review Board through October 1999</p>						
ISA13	I12	Interchange Control Number	M	N0	9/9	Must use
<p>Description: A control number assigned by the interchange sender</p>						
ISA14	I13	Acknowledgment Requested	M	ID	1/1	Must use
<p>Description: Code indicating sender's request for an interchange acknowledgment</p> <p>Code List Summary (Total Codes: 2, Included: 1)</p> <p>Code Name</p> <p>0 No Acknowledgment Requested</p>						
ISA15	I14	Usage Indicator	M	ID	1/1	Must use
<p>Description: Code indicating whether data enclosed by this interchange envelope is test, production or information</p> <p>Code List Summary (Total Codes: 3, Included: 2)</p> <p>Code Name</p> <p>P Production Data</p> <p>T Test Data</p>						
ISA16	I15	Component Element Separator	M		1/1	Must use

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
------------	-----------	---------------------	------------	-------------	----------------	--------------

Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator

Notes: *Element separator:* *

Segment terminator: ~

Component separator: >

GS Functional Group Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

User Option (Usage): Must use

Purpose: To indicate the beginning of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS01	479	Functional Identifier Code	M	ID	2/2	Must use
		Description: Code identifying a group of application related transaction sets				
		Code List Summary (Total Codes: 263, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		PO	Purchase Order (850)			
GS02	142	Application Sender's Code	M	AN	2/15	Must use
		Description: Code identifying party sending transmission; codes agreed to by trading partners				
		Notes: FAMILYDOLLAR				
GS03	124	Application Receiver's Code	M	AN	2/15	Must use
		Description: Code identifying party receiving transmission; codes agreed to by trading partners				
		Notes: Receiver ID				
GS04	373	Date	M	DT	8/8	Must use
		Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year				
GS05	337	Time	M	TM	4/8	Must use
		Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)				
GS06	28	Group Control Number	M	N0	1/9	Must use
		Description: Assigned number originated and maintained by the sender				
GS07	455	Responsible Agency Code	M	ID	1/2	Must use
		Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480				
		Code List Summary (Total Codes: 2, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		X	Accredited Standards Committee X12			
GS08	480	Version / Release / Industry Identifier Code	M	AN	1/12	Must use

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
------------	-----------	---------------------	------------	-------------	----------------	--------------

Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed

Code List Summary (Total Codes: 41, Included: 1)

<u>Code</u>	<u>Name</u>
-------------	-------------

004030	Draft Standards Approved for Publication by ASC X12 Procedures Review Board through October 1999
--------	--

Semantics:

1. GS04 is the group date.
2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

ST Transaction Set Header

Pos: 0100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use
Description: Code uniquely identifying a Transaction Set						
Code List Summary (Total Codes: 314, Included: 1)						
<u>Code</u> <u>Name</u>						
850 Purchase Order						
ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set						

Semantics:

1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition.

BEG Beginning Segment for Purchase Order

Pos: 0200	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 5

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>								
BEG01	353	Transaction Set Purpose Code	M	ID	2/2	Must use								
<p>Description: Code identifying purpose of transaction set</p> <p>Code List Summary (Total Codes: 65, Included: 3)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>00</td> <td>Original</td> </tr> <tr> <td>01</td> <td>Cancellation</td> </tr> <tr> <td>05</td> <td>Replace</td> </tr> </tbody> </table>							<u>Code</u>	<u>Name</u>	00	Original	01	Cancellation	05	Replace
<u>Code</u>	<u>Name</u>													
00	Original													
01	Cancellation													
05	Replace													
BEG02	92	Purchase Order Type Code	M	ID	2/2	Must use								
<p>Description: Code specifying the type of Purchase Order</p> <p>Code List Summary (Total Codes: 71, Included: 1)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>NE</td> <td>New Order</td> </tr> </tbody> </table>							<u>Code</u>	<u>Name</u>	NE	New Order				
<u>Code</u>	<u>Name</u>													
NE	New Order													
BEG03	324	Purchase Order Number	M	AN	1/22	Must use								
<p>Description: Identifying number for Purchase Order assigned by the orderer/purchaser</p>														
BEG04	328	Release Number	O	AN	1/30	Used								
<p>Description: Number identifying a release against a Purchase Order previously placed by the parties involved in the transaction</p>														
BEG05	373	Date	M	DT	8/8	Must use								
<p>Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year</p>														

Semantics:

1. BEG05 is the date assigned by the purchaser to purchase order.

REF Reference Identification

Pos: 0500	Max: >1
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

Purpose: To specify identifying information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
REF01	128	Reference Identification Qualifier	M	ID	2/3	Must use
Description: Code qualifying the Reference Identification						
Code List Summary (Total Codes: 1631, Included: 1)						
Code Name						
VR Vendor ID Number						
REF02	127	Reference Identification	X	AN	1/50	Used
Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier						
Notes: <i>Vendor Name</i>						

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

REF Reference Identification

Pos: 0500	Max: >1
Heading - Optional	
Loop: N/A	Elements: 3

User Option (Usage): Used

Purpose: To specify identifying information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
REF01	128	Reference Identification Qualifier	M	ID	2/3	Must use
		Description: Code qualifying the Reference Identification				
		Code List Summary (Total Codes: 1631, Included: 1)				
		<u>Code</u>		<u>Name</u>		
		06		System Number		
REF02	127	Reference Identification	X	AN	1/50	Used
		Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier				
REF03	352	Description	X	AN	1/80	Used
		Description: A free-form description to clarify the related data elements and their content				

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

REF Reference Identification

Pos: 0500	Max: >1
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

Purpose: To specify identifying information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
REF01	128	Reference Identification Qualifier	M	ID	2/3	Must use
Description: Code qualifying the Reference Identification						
Code List Summary (Total Codes: 1631, Included: 1)						
Code Name						
MR Merchandise Type Code						
REF02	127	Reference Identification	X	AN	1/50	Used
Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier						

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

PER Administrative Communications Contact

Pos: 0600	Max: 3
Heading - Optional	
Loop: N/A	Elements: 4

User Option (Usage): Used

Purpose: To identify a person or office to whom administrative communications should be directed

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PER01	366	Contact Function Code	M	ID	2/2	Must use
		Description: Code identifying the major duty or responsibility of the person or group named				
		Code List Summary (Total Codes: 234, Included: 1)				
		Code		Name		
		TA		Traffic Administrator		
PER02	93	Name	O	AN	1/60	Used
		Description: Free-form name				
PER03	365	Communication Number Qualifier	X	ID	2/2	Used
		Description: Code identifying the type of communication number				
		Code List Summary (Total Codes: 40, Included: 1)				
		Code		Name		
		TE		Telephone		
PER04	364	Communication Number	X	AN	1/256	Used
		Description: Complete communications number including country or area code when applicable				

Syntax Rules:

1. P0304 - If either PER03 or PER04 is present, then the other is required.
2. P0506 - If either PER05 or PER06 is present, then the other is required.
3. P0708 - If either PER07 or PER08 is present, then the other is required.

FOB F.O.B. Related Instructions

Pos: 0800	Max: >1
Heading - Optional	
Loop: N/A	Elements: 3

User Option (Usage): Used

Purpose: To specify transportation instructions relating to shipment

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
FOB01	146	Shipment Method of Payment	M	ID	2/2	Must use
		Description: Code identifying payment terms for transportation charges				
		Code List Summary (Total Codes: 31, Included: 6)				
		Code		Name		
		CC		Collect		
		CD		Collect on Delivery		
		DF		Defined by Buyer and Seller		
		MX		Mixed		
		PC		Prepaid but Charged to Customer		
		PP		Prepaid (by Seller)		
FOB06	309	Location Qualifier	X	ID	1/2	Used
		Description: Code identifying type of location				
		Code List Summary (Total Codes: 176, Included: 1)				
		Code		Name		
		DE		Destination (Shipping)		
FOB07	352	Description	O	AN	1/80	Used
		Description: A free-form description to clarify the related data elements and their content				

Syntax Rules:

1. C0302 - If FOB03 is present, then FOB02 is required.
2. C0405 - If FOB04 is present, then FOB05 is required.
3. C0706 - If FOB07 is present, then FOB06 is required.
4. C0809 - If FOB08 is present, then FOB09 is required.

Semantics:

1. FOB01 indicates which party will pay the carrier.
2. FOB02 is the code specifying transportation responsibility location.
3. FOB06 is the code specifying the title passage location.
4. FOB08 is the code specifying the point at which the risk of loss transfers. This may be different than the location specified in FOB02/FOB03 and FOB06/FOB07.

ITD Terms of Sale/Deferred Terms of Sale

Pos: 1300	Max: >1
Heading - Optional	
Loop: N/A	Elements: 1

User Option (Usage): Used

Purpose: To specify terms of sale

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ITD12	352	Description	O	AN	1/80	Used

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. L03040513 - If ITD03 is present, then at least one of ITD04, ITD05 or ITD13 is required.
2. L08040513 - If ITD08 is present, then at least one of ITD04, ITD05 or ITD13 is required.
3. L091011 - If ITD09 is present, then at least one of ITD10 or ITD11 is required.

Semantics:

1. ITD15 is the percentage applied to a base amount used to determine a late payment charge.

Comments:

1. If the code in ITD01 is "04", then ITD07 or ITD09 is required and either ITD10 or ITD11 is required; if the code in ITD01 is "05", then ITD06 or ITD07 is required.

DTM Date/Time Reference

Pos: 1500	Max: 10
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

Purpose: To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>				
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use				
<p>Description: Code specifying type of date or time, or both date and time</p> <p>Code List Summary (Total Codes: 1226, Included: 1)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>037</td> <td>Ship Not Before</td> </tr> </tbody> </table>							<u>Code</u>	<u>Name</u>	037	Ship Not Before
<u>Code</u>	<u>Name</u>									
037	Ship Not Before									
DTM02	373	Date	X	DT	8/8	Used				
<p>Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year</p>										

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

DTM Date/Time Reference

Pos: 1500	Max: 10
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

Purpose: To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>				
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use				
<p>Description: Code specifying type of date or time, or both date and time</p> <p>Code List Summary (Total Codes: 1226, Included: 1)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>017</td> <td>Estimated Delivery</td> </tr> </tbody> </table>							<u>Code</u>	<u>Name</u>	017	Estimated Delivery
<u>Code</u>	<u>Name</u>									
017	Estimated Delivery									
DTM02	373	Date	X	DT	8/8	Used				
<p>Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year</p>										

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

DTM Date/Time Reference

Pos: 1500	Max: 10
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

Purpose: To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use
Description: Code specifying type of date or time, or both date and time						
Code List Summary (Total Codes: 1226, Included: 1)						
Code Name						
038 Ship No Later						
DTM02	373	Date	X	DT	8/8	Used
Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year						

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

DTM Date/Time Reference

Pos: 1500	Max: 10
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

Purpose: To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>				
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use				
<p>Description: Code specifying type of date or time, or both date and time</p> <p>Code List Summary (Total Codes: 1226, Included: 1)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>061</td> <td>Cancel if Not Delivered by</td> </tr> </tbody> </table>							<u>Code</u>	<u>Name</u>	061	Cancel if Not Delivered by
<u>Code</u>	<u>Name</u>									
061	Cancel if Not Delivered by									
DTM02	373	Date	X	DT	8/8	Used				
<p>Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year</p>										

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

TD5 Carrier Details (Routing Sequence/Transit Time)

Pos: 2400	Max: >1
Heading - Optional	
Loop: N/A	Elements: 3

User Option (Usage): Used

Purpose: To specify the carrier and sequence of routing and provide transit time information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>				
TD505	387	Routing	X	AN	1/35	Used				
<p>Description: Free-form description of the routing or requested routing for shipment, or the originating carrier's identity</p> <p>Notes: www.familydollar.com/pdfs/rsp.pdf</p>										
TD507	309	Location Qualifier	O	ID	1/2	Used				
<p>Description: Code identifying type of location</p> <p>Code List Summary (Total Codes: 176, Included: 1)</p> <table border="1"> <thead> <tr> <th><u>Code</u></th> <th><u>Name</u></th> </tr> </thead> <tbody> <tr> <td>ZZ</td> <td>Mutually Defined</td> </tr> </tbody> </table>							<u>Code</u>	<u>Name</u>	ZZ	Mutually Defined
<u>Code</u>	<u>Name</u>									
ZZ	Mutually Defined									
TD508	310	Location Identifier	X	AN	1/30	Used				
<p>Description: Code which identifies a specific location</p>										

Syntax Rules:

1. R0204050612 - At least one of TD502, TD504, TD505, TD506 or TD512 is required.
2. C0203 - If TD502 is present, then TD503 is required.
3. C0708 - If TD507 is present, then TD508 is required.
4. C1011 - If TD510 is present, then TD511 is required.
5. C1312 - If TD513 is present, then TD512 is required.
6. C1413 - If TD514 is present, then TD513 is required.
7. C1512 - If TD515 is present, then TD512 is required.

Semantics:

1. TD515 is the country where the service is to be performed.

Comments:

1. When specifying a routing sequence to be used for the shipment movement in lieu of specifying each carrier within the movement, use TD502 to identify the party responsible for defining the routing sequence, and use TD503 to identify the actual routing sequence, specified by the party identified in TD502.

N1 Name

Pos: 3100	Max: 1
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

Code List Summary (Total Codes: 1446, Included: 1)

Code Name

VN Vendor

N102	93	Name	X	AN	1/60	Used
------	----	-------------	---	----	------	------

Description: Free-form name

Notes: *Vendor Name*

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Address Information

Pos: 3300	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used

Purpose: To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/55	Must use
		Description: Address information				
N302	166	Address Information	O	AN	1/55	Used
		Description: Address information				

Notes:

Vendor Address

N4 Geographic Location

Pos: 3400	Max: >1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Used
		Description: Free-form text for city name				
N402	156	State or Province Code	X	ID	2/2	Used
		Description: Code (Standard State/Province) as defined by appropriate government agency				
N403	116	Postal Code	O	ID	3/15	Used
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				

Syntax Rules:

1. E0207 - Only one of N402 or N407 may be present.
2. C0605 - If N406 is present, then N405 is required.
3. C0704 - If N407 is present, then N404 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

Notes:

Vendor's City, State and Zip

N1 Name

Pos: 3100	Max: 1
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

Code List Summary (Total Codes: 1446, Included: 1)

Code Name

RI Remit To

N102	93	Name	X	AN	1/60	Used
------	----	-------------	---	----	------	------

Description: Free-form name

Notes: *Vendor's Remit Name*

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Address Information

Pos: 3300	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used

Purpose: To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/55	Must use
		Description: Address information				
N302	166	Address Information	O	AN	1/55	Used
		Description: Address information				

Notes:

Vendor's Remit Address

N4 Geographic Location

Pos: 3400	Max: >1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Used
		Description: Free-form text for city name				
N402	156	State or Province Code	X	ID	2/2	Used
		Description: Code (Standard State/Province) as defined by appropriate government agency				
N403	116	Postal Code	O	ID	3/15	Used
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				

Syntax Rules:

1. E0207 - Only one of N402 or N407 may be present.
2. C0605 - If N406 is present, then N405 is required.
3. C0704 - If N407 is present, then N404 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

Notes:

Vendor's Remit City, State and ZIP

N1 Name

Pos: 3100	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

User Option (Usage): Used

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use
		Description: Code identifying an organizational entity, a physical location, property or an individual				
		Code List Summary (Total Codes: 1446, Included: 1)				
		Code Name				
		BT Bill-to-Party				
N102	93	Name	X	AN	1/60	Used
		Description: Free-form name				
		Notes: <i>Family Dollar Stores, Inc.</i>				
N103	66	Identification Code Qualifier	X	ID	1/2	Used
		Description: Code designating the system/method of code structure used for Identification Code (67)				
		Code List Summary (Total Codes: 223, Included: 1)				
		Code Name				
		1 D-U-N-S Number, Dun & Bradstreet				
N104	67	Identification Code	X	AN	2/80	Used
		Description: Code identifying a party or other code				
		Notes: <i>024472631</i>				

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Address Information

Pos: 3300	Max: 2
Heading - Optional	
Loop: N1	Elements: 1

User Option (Usage): Used

Purpose: To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/55	Must use

Description: Address information

Notes: P. O. Box 1017

N4 Geographic Location

Pos: 3400	Max: >1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Used
		Description: Free-form text for city name				
		Notes: <i>Charlotte</i>				
N402	156	State or Province Code	X	ID	2/2	Used
		Description: Code (Standard State/Province) as defined by appropriate government agency				
		Notes: <i>NC</i>				
N403	116	Postal Code	O	ID	3/15	Used
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				
		Notes: <i>28201-101</i>				

Syntax Rules:

1. E0207 - Only one of N402 or N407 may be present.
2. C0605 - If N406 is present, then N405 is required.
3. C0704 - If N407 is present, then N404 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

N1 Name

Pos: 3100	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

User Option (Usage): Used

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

Code List Summary (Total Codes: 1446, Included: 1)

Code Name

ST Ship To

N102	93	Name	X	AN	1/60	Used
------	----	-------------	---	----	------	------

Description: Free-form name

N103	66	Identification Code Qualifier	X	ID	1/2	Used
------	----	--------------------------------------	---	----	-----	------

Description: Code designating the system/method of code structure used for Identification Code (67)

Code List Summary (Total Codes: 223, Included: 2)

Code Name

9 D-U-N-S+4, D-U-N-S Number with Four Character Suffix

Notes:

Use for Warehouse Vendors

92 Assigned by Buyer or Buyer's Agent

Notes:

Use for DSD Vendors

N104	67	Identification Code	X	AN	2/80	Used
------	----	----------------------------	---	----	------	------

Description: Code identifying a party or other code

Notes: *Store Five Digit Location Number - DSD*

DUNS+4 - Warehouse Vendor

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Address Information

Pos: 3300	Max: 2
Heading - Optional	
Loop: N1	Elements: 1

User Option (Usage): Used

Purpose: To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/55	Must use

Description: Address information

Notes:

Store Location Address

N4 Geographic Location

Pos: 3400	Max: >1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Used
		Description: Free-form text for city name				
N402	156	State or Province Code	X	ID	2/2	Used
		Description: Code (Standard State/Province) as defined by appropriate government agency				
N403	116	Postal Code	O	ID	3/15	Used
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				

Syntax Rules:

1. E0207 - Only one of N402 or N407 may be present.
2. C0605 - If N406 is present, then N405 is required.
3. C0704 - If N407 is present, then N404 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

Notes:

Store Location City, State and ZIP

PO1 Baseline Item Data

Pos: 0100	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 11

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	Assigned Identification	O	AN	1/20	Used
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
PO102	330	Quantity Ordered	X	R	1/15	Used
		Description: Quantity ordered				
PO103	355	Unit or Basis for Measurement Code	O	ID	2/2	Used
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		Code List Summary (Total Codes: 803, Included: 2)				
		<u>Code</u> <u>Name</u>				
		CA Case				
		EA Each				
PO104	212	Unit Price	X	R	1/17	Used
		Description: Price per unit of product, service, commodity, etc.				
PO105	639	Basis of Unit Price Code	O	ID	2/2	Used
		Description: Code identifying the type of unit price for an item				
		Code List Summary (Total Codes: 91, Included: 1)				
		<u>Code</u> <u>Name</u>				
		PE Price per Each				
PO106	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		Code List Summary (Total Codes: 505, Included: 1)				
		<u>Code</u> <u>Name</u>				
		SK Stock Keeping Unit (SKU)				
PO107	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				
		Notes: <i>Family Dollar SKU</i>				
PO108	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
		Code List Summary (Total Codes: 505, Included: 1)				
		Code Name				
		ST Style Number				
PO109	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				
		Notes: <i>Vendor's Style Number or NA</i>				
PO110	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		Code List Summary (Total Codes: 505, Included: 1)				
		Code Name				
		UP UCC - 12				
		Description: <i>Data structure for the 12 digit EAN.UCC (EAN International.Uniform Code Council) Global Trade Identification Number (GTIN). Also known as the Universal Product Code (U.P.C.)</i>				
PO111	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

CTP Pricing Information

Pos: 0400	Max: 1
Detail - Optional	
Loop: CTP	Elements: 2

User Option (Usage): Used

Purpose: To specify pricing information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTP02	236	Price Identifier Code	X	ID	3/3	Used
Description: Code identifying pricing specification						
Code List Summary (Total Codes: 167, Included: 1)						
<u>Code</u> <u>Name</u>						
RTL Retail						
CTP03	212	Unit Price	X	R	1/17	Used
Description: Price per unit of product, service, commodity, etc.						

Syntax Rules:

1. P0405 - If either CTP04 or CTP05 is present, then the other is required.
2. C0607 - If CTP06 is present, then CTP07 is required.
3. C0902 - If CTP09 is present, then CTP02 is required.
4. C1002 - If CTP10 is present, then CTP02 is required.
5. C1103 - If CTP11 is present, then CTP03 is required.

Semantics:

1. CTP07 is a multiplier factor to arrive at a final discounted price. A multiplier of .90 would be the factor if a 10% discount is given.
2. CTP08 is the rebate amount.

Comments:

1. See Figures Appendix for an example detailing the use of CTP03 and CTP04.
2. See Figures Appendix for an example detailing the use of CTP03, CTP04 and CTP07.

PID Product/Item Description

Pos: 0500	Max: 1
Detail - Optional	
Loop: PID	Elements: 2

User Option (Usage): Used

Purpose: To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID01	349	Item Description Type	M	ID	1/1	Must use
		Description: Code indicating the format of a description				
		Code List Summary (Total Codes: 3, Included: 1)				
		<u>Code</u>		<u>Name</u>		
		F		Free-form		
PID05	352	Description	X	AN	1/80	Used
		Description: A free-form description to clarify the related data elements and their content				

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.
3. PID07 specifies the individual code list of the agency specified in PID03.

PO4 Item Physical Details

Pos: 0900	Max: >1
Detail - Optional	
Loop: PO1	Elements: 2

User Option (Usage): Used

Purpose: To specify the physical qualities, packaging, weights, and dimensions relating to the item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO401	356	Pack	O	NO	1/6	Used
		Description: The number of inner containers, or number of eaches if there are no inner containers, per outer container				
PO414	810	Inner Pack	O	NO	1/6	Used
		Description: The number of eaches per inner container				

Syntax Rules:

1. P0203 - If either PO402 or PO403 is present, then the other is required.
2. C0506 - If PO405 is present, then PO406 is required.
3. P0607 - If either PO406 or PO407 is present, then the other is required.
4. P0809 - If either PO408 or PO409 is present, then the other is required.
5. C1013 - If PO410 is present, then PO413 is required.
6. C1113 - If PO411 is present, then PO413 is required.
7. C1213 - If PO412 is present, then PO413 is required.
8. L13101112 - If PO413 is present, then at least one of PO410, PO411 or PO412 is required.
9. C1716 - If PO417 is present, then PO416 is required.
10. C1804 - If PO418 is present, then PO404 is required.

Semantics:

1. PO415 is used to indicate the relative layer of this package or range of packages within the layers of packaging. Relative Position 1 (value R1) is the innermost package.
2. PO416 is the package identifier or the beginning package identifier in a range of identifiers.
3. PO417 is the ending package identifier in a range of identifiers.
4. PO418 is the number of packages in this layer.

Comments:

1. PO403 - The "Unit or Basis for Measure Code" in this segment position is for purposes of defining the unit of measure of the "Size" identified in the PO402. For example: If the carton contains 24 12-Ounce packages, it would be described as follows: Data element 356 = "24"; Data element 357 = "12"; Data element 355 = "OZ".
2. PO413 defines the unit of measure for PO410, PO411, and PO412.

CTT Transaction Totals

Pos: 0100	Max: 1
Summary - Optional	
Loop: CTT	Elements: 2

User Option (Usage): Used

Purpose: To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	NO	1/6	Must use
		Description: Total number of line items in the transaction set				
CTT02	347	Hash Total	O	R	1/10	Used
		Description: Sum of values of the specified data element. All values in the data element will be summed without regard to decimal points (explicit or implicit) or signs. Truncation will occur on the left most digits if the sum is greater than the maximum size of the hash total of the data element. Example: -.0018 First occurrence of value being hashed. .18 Second occurrence of value being hashed. 1.8 Third occurrence of value being hashed. 18.01 Fourth occurrence of value being hashed. ----- 1855 Hash Total				

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

AMT Monetary Amount

Pos: 0200	Max: 1
Summary - Optional	
Loop: CTT	Elements: 2

User Option (Usage): Used

Purpose: To indicate the total monetary amount

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
AMT01	522	Amount Qualifier Code	M	ID	1/3	Must use
		Description: Code to qualify amount				
		Code List Summary (Total Codes: 1696, Included: 1)				
		<u>Code</u>		<u>Name</u>		
		TT		Total Transaction Amount		
AMT02	782	Monetary Amount	M	R	1/18	Must use
		Description: Monetary amount				

SE Transaction Set Trailer

Pos: 0300	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	NO	1/10	Must use
		Description: Total number of segments included in a transaction set including ST and SE segments				
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

Comments:

1. SE is the last segment of each transaction set.

GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	Number of Transaction Sets Included	M	NO	1/6	Must use
		Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element				
GE02	28	Group Control Number	M	NO	1/9	Must use
		Description: Assigned number originated and maintained by the sender				

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	116	Number of Included Functional Groups	M	NO	1/5	Must use
		Description: A count of the number of functional groups included in an interchange				
IEA02	112	Interchange Control Number	M	NO	9/9	Must use
		Description: A control number assigned by the interchange sender				